



INTEGRA 406 GPS ELT PACK

EDMO #: 1202502

MFR #: N/A

The INTEGRA 406 GPS ELT (Emergency Locator Transmitter) is the newest addition to the Kannad Aviation emergency distress beacon family.

Includes:

- ELT
- Universal Mounting Bracket
- RC200 Remote Control Switch Kit
- DIN12 Connector

Features:

- Integrated internal 406MHz antenna
- Unique built in GPS
- Compact size
- Operates at temperatures as low as -20 °C, with 24 hour certified transmission on 406MHz (distress) signal and over 48 hours on 121.5MHz (homing) signal
- No external power supply required
- Choice of Remote Control Panels with 3-wire and 2-wire installation options
- Quick and easy retrofit with universal mounting bracket
- Minor change approval available for most common aircraft
- 6 year replaceable battery
- Optional programming dongle, perfect for fleet operators

INTEGRA 406 GPS ELT PACK SPECIFICATIONS

Automatic Fixed Emergency Locator Transmitter with G-Switch sensor

Two-frequency ELT (121.5 / 406.037 MHz)
COSPAS –SARSAT Class 2 (-20°C to +55°C)
RTCA DO-160/EUROCAE ED14 Environmental conditions

Autonomy:
Minimum operational duration at -20°C is 24 hours on 406MHz and over 48 hours on 121.5MHz

Controls and indicators:
ARM/OFF/ON switch
Bright red LED
Internal Buzzer
Outside Buzzer option

Interfaces:
DIN12 socket for remote control panel (RCP)
Pin programming option
BNC antenna connector

Battery:
Replacement Interval every 6 years

Accessories directly powered by ELT battery

Unique functions:

Integrated 406 antenna

GPS built-in (antenna & receiver)

Housing:

Material:

Molded plastic

Color:

Yellow (Color compounded)

Dimensions:

Installed with mounting bracket 175 x 99 x 88.4mm (6.89 x 3.90 x 3.40 in.)

Weight including batteries:

Typical 850g (1.873lb) Max 875g (1.929lb)